

Sensor Transmitter Module STM 431T - PRELIMINARY

The extremely power saving RF transmitter modules STM 431T of EnOcean are optimized for realization of wireless and maintenance free temperature sensors, or room operating panels including set point dial and occupancy button with a minimum number of external components. The modules provide an integrated calibrated temperature sensor.

Functional Principle

Power supply is provided by a small solar cell, an external energy harvester, or an external 3V battery. An energy storage element is installed to bridge periods with no supply from the energy harvester. The module provides a user configurable cyclic wake up.

After wake up a radio telegram will be transmitted in case of a significant change of measured temperature or set point values or if the external occupancy button is pressed.



The firmware can be configured to use different EEPs according to the availability set point dial and occupancy button.

STM 431T modules also support the plug-in humidity sensor module HSM 100. The module can be switched to enhanced security mode with encrypted communication.

Type
STM 431T

Ordering Code
S3041-D431

Features Overview

Power supply	Pre-installed solar cell
Antenna	Helix antenna (STM 431T)
Frequency	921.4 MHz
Conducted Output Power	typ. 0 dBm
Data rate / Modulation type	125 kbps FSK
Start-up time with empty energy storage	typ. <2.5 min @ 400 lux, 25 °C
Operation time in darkness @25°C¹	min. 10 days, if energy storage fully charged ¹
Input Channels	Internal: temperature sensor, LRN button External via 20 pin connector: occupancy button, set point dial, HSM 100
Temperature sensor	Measurement range 0-40 °C, resolution 0.16 K Accuracy typ. ±0.5 K between 17 °C and 27 °C, typ. ±1 K between 0 °C and 40°C
Transmission indicator	1x LED
EnOcean Equipment profiles	configurable EEPs: A5-02-05, A5-10-05, A5-10-03 and with HSM 100: A5-04-01, A5-10-10, A5-10-12
Module dimensions	43 x 16 x 8 mm
Operating temperature¹	-20 up to +60 °C
Security Level Format	24-bit RLC, RLC tx, 3-byte CMAC, VAES encryption

¹ At default configuration (wake-up cycle 100 s, transmission cycle 1000 s).